



Programming the Toggle Function of the 5900 Series Door Operator

1. Disconnect the 120volt power plug from main control unit.
2. Press the Learn button (LRN)
3. While pressing (LRN), connect the electrical power plug.
4. Watch the "Error LED"
5. Release the Learn button after 5 seconds (LED is OUT)
6. The LED will flash once, pause and repeat (continuously). This indicates the control unit is in Parameter #1.
7. Pressing the LRN button again will increase the Parameter by 1.
8. The Toggle function is Parameter 8; press LRN until you see 8 flashes then a pause then 8 more flashes.
9. Once you see 8 flashes, disconnect the 120volt power plug from the main control unit.
10. Wait 10 seconds; connect the electrical power plug.
11. The unit is now in Parameter 8 Toggle function (active).

NOTE: Toggle Hold Open Feature is 15 Min Max Unit will close Automatically after 15 Min